

LT6711GX --- Product Brief

HDMI2.1 to DP1.4 with Type-C

Features

- **HDMI2.1 Receiver**
 - Compliant with the HDMI 2.1 specification
 - Support FRL mode with 3, 6 or 8Gbps Data Rate
 - Support HDCP 1.4/2.2/2.3
 - Support HDR
 - Support FEC
 - Support DDC, SCDC and CEC
 - Support 8k@30Hz, 8k@60Hz with DSC
- **DP1.4 Transmitter**
 - Compliant to VESA DP1.4 Standard
 - Support Four Lanes with 1.62, 2.7, 5.4 or 8.1Gbps Data Rate
 - Data Lane and Polarity Swapping
 - Support HDCP 1.3/2.2/2.3
 - Support HDR
 - Support FEC
 - Support 8k@30Hz, 8k@60Hz with DSC
 - Support Backlight Control & MCCS over AUX for eDP
 - Support ASSR for eDP
 - Support 8 Lane eDP
 - Build-in Pattern Generation
- **USB Type-C**
 - Compliant with VESA DisplayPort Alt Mode on USB Type-C standard V1.0b
 - DP Alt Mode only support pin assignment C、E
 - Compliant with USB Power Delivery specification R3.0, V1.0
 - Compliant with USB Type-C specification R1.3
 - Built-in CC controller for charger and normal communication
 - CC controller supported: DFP and DRP

- Support FR Swap
- **Miscellaneous**
 - External oscillator
 - Integrated microprocessor
 - Embedded SPI flash for firmware
 - GPIOs for VBUS/VCONN/AUX and other system controls
 - Integrated 100/400kHz I2C slave
 - Low power consumption
 - Power supply: 3.3V for I/O and 1.1V for core
 - Package: 10mmx10mm QFN88

Description

The Lontium LT6711GX is HDMI2.1 to DP1.4 converter with internal Type-C Alternate Mode switch and PD controller.

For HDMI input, it consists of 4 data lanes, support 3, 6 or 8Gbps link speeds. It allow for the highest resolutions of 8K@60Hz with DSC or 8K@30Hz.

For DP1.4 output, it consists of 4 data lanes, support 1.62, 2.7, 5.4 or 8.1Gbps link speeds. The build-in optional SSC function reduces EMI effect.

In order to be adaptable to the latest USB Type-C system, LT6711GX integrates a high performance bi-directional Super-Speed controlled by CC logic and PD management unit to relieve mobile system design complexity and BOM cost.

The LT6711GX is fabricated in advanced CMOS process and implemented in 10mmx10mm QFN88 package. This package is RoHS compliant and specified to operate from -40°C to +85°C.

Applications

- Mobile systems, VR/AR
- Cellular handsets, PAD/Tablets
- Digital video cameras and Digital still cameras



Figure 1. Application Diagram

Ordering Information

Part Number	Operating Temperature Range	Package	Packing Method
LT6711GX	-40°C to+85°C	QFN88 (10*10)	Tray

Copyright © 2019 Lontium Semiconductor Corporation, All rights reserved.

Lontium Semiconductor Proprietary & Confidential

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT, MERCHANTABILITY, TITLE AND FITNESS FOR A PARTICULAR PURPOSE. CUSTOMERS EXPRESSLY ASSUME THEIR OWN RISK IN RELYING ON THIS DOCUMENT.

LONTIUM PRODUCTS ARE NOT DESIGNED OR INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS WHERE A MALFUNCTION OF A LONTIUM DEVICE COULD RESULT IN A PERSONAL INJURY OR LOSS OF LIFE.

Lontium assumes no responsibility for any errors in this document, and makes no commitment to update the information contained herein. Lontium reserves the right to change or discontinue this document and the products it describes at any time, without notice. Other than as set forth in a separate, signed, written agreement, Lontium grants the user of this document no right, title or interest in the document, the information it contains or the intellectual property in embodies.

Trademarks

Lontium™ 龙迅™ and ClearEdge™ is a registered trademark of Lontium Semiconductor. All Other brand names, product names, trademarks, and registered trademarks contained herein are the property of their respective owners.

Visit our corporate web page at: www.lontiumsemi.com

Technical support: support@lontium.com

Sales: sales@lontium.com