

# LT8711H-C --- Product Brief

## DP to HDMI Converter with USB Type - C Support

### Features

- **DisplayPort receiver**
  - DP 1.2 compliant
  - HDCP 1.3 compliant
  - Link rate 5.4/2.7/1.62Gbps (HBR2/HBR/RBR)
  - 1/2/4 lanes
  - Integrated CC controller for USB type-C Alt Mode support
  - 1Mbps AUX channel
  - Equalizer
- **HDMI transmitter**
  - HDMI 1.4 compliant
  - DVI 1.0 compliant
  - AC-couple capable
  - Data rate up to 3Gbps
  - FHD 1080p 60Hz 3D
  - UHD 4k 30Hz
  - Pre-emphasis
  - Downstream RX sensing
  - Output swing calibration
  - 5V tolerance DDC/HPD I/Os
- **Miscellaneous**
  - Integrated MCU with embedded SPI flash

- Power supply: 3.3V for I/O and 1.2V for core
- 64-pin QFN package

### Description

The LT8711H-C is a DisplayPort(DP) to HDMI converter, designed to connect a DP source to a HDMI sink. The LT8711H-C integrates a DP 1.2 compliant receiver, and a HDMI 1.4 compliant transmitter. The receiver port integrates a CC controller which enables DP Alternate Mode support when connected to a USB Type-C source.

The device is capable of automatic operation that is enabled by an integrated MCU that uses an embedded SPI flash for microcode. System control is also available through the use of a dedicated configuration I2C slave interface.

LT8711H-C is provided in a 64-lead QFN package with ePad and specified over -40°C to +85°C operating temperature range.

### Applications

- Docking station
- DP-to-HDMI dongle/adaptor



Type-C to HDMI1.4



DP to HDMI1.4

Figure 1. Application Diagrams

## Ordering Information

Part Number	Operating Temperature Range	Package	Packing Method
LT8711H-C	-40°C to +85°C	QFN64 (7.5*7.5)	Tray

LONTIUM CONFIDENTIAL

**Copyright © 2016-2019 Lontium Semiconductor Corporation, All rights reserved.**

### **Lontium Semiconductor Proprietary & Confidential**

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT, MERCHANTABILITY, TITLE AND FITNESS FOR A PARTICULAR PURPOSE. CUSTOMERS EXPRESSLY ASSUME THEIR OWN RISK IN RELYING ON THIS DOCUMENT.

LONTIUM PRODUCTS ARE NOT DESIGNED OR INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS WHERE A MALFUNCTION OF A LONTIUM DEVICE COULD RESULT IN A PERSONAL INJURY OR LOSS OF LIFE.

Lontium assumes no responsibility for any errors in this document, and makes no commitment to update the information contained herein. Lontium reserves the right to change or discontinue this document and the products it describes at any time, without notice. Other than as set forth in a separate, signed, written agreement, Lontium grants the user of this document no right, title or interest in the document, the information it contains or the intellectual property in embodies.

### **Trademarks**

Lontium™ 龙迅™ and ClearEdge™ is a registered trademark of Lontium Semiconductor. All Other brand names, product names, trademarks, and registered trademarks contained herein are the property of their respective owners.

**Visit our corporate web page at: [www.lontiumsemi.com](http://www.lontiumsemi.com)**

**Technical support: [support@lontium.com](mailto:support@lontium.com)**

**Sales: [sales@lontium.com](mailto:sales@lontium.com)**